

L3HARRIS 12500-2500-0X

Smart Battery for Handheld Radios

| GENERAL | |
|-------------------|---|
| RT Nomenclature | 12500-2500-0X |
| Compatibility | RF-7850S, RF-7850M, AN/PRC-152A, AN/PRC-163, RF-7800V |
| Charging Voltage | 12.7 V |
| Output Voltage | 7.2 - 12.7 V Operating |
| Battery Capacity | 7 Ah |
| Maximum Discharge | 8.5 A continuous |
| Total Power | 72 Wh |

| BH7f0036c -0036w 8 0 84 1 scn/GS0 gs/T11 1 Tf1 10/S04e1279390(a)-10scn3 004 | |
|---|--|
| | |
| | |
| | |

The 12500-2500-0X features SMBus connectivity, providing more accurate battery status and calibration information with other devices including chargers, analyzers and vehicular adapters. The Smart Battery for Handheld Radios also features a non-light-emitting LED display, giving users a quick indication of remaining power without having to put it on an analyzer or charger. The 12500-2500-0X is compatible with Falcon III® radios and is engineered to meet the high-power demands of L3Harris dual-channel handhelds.

